

Program: BBA in Technology Management (4th Sem)

Semester: Summer

Date: 15 May, 2023 (Monday) Time: 10:00 am - 1:00 pm

ISLAMIC UNIVERSITY OF TECHNOLOGY (IUT)

ORGANISATION OF ISLAMIC COOPERATION (OIC)

DEPARTMENT OF MECHANICAL AND PRODUCTION ENGINEERING

Semester Final Examination Course Number: MCE 4461

Course Title: Mechanical Technology II

Winter Semester: 2021 - 2022

Full Marks: 150 Time: 3 Hours

There are six questions. Answer all the questions. The symbols have their usual meanings. Marks of each question and corresponding CO and PO are written in the brackets. Assume reasonable value of missing data.

1. a. Draw sketches to illustrate the dynamic characteristics of the following: (12+8+5=25)

Zero-order instrument

First-order instrument ii.

CO₁ PO1,PO2

- iii. Second-order instrument
- In the case of a second-order instrument, indicate the effect of different degrees of damping on the time response.
- Draw the block diagram of flow rate, speed measurement, temperature measurement and weight measurement system and indicate different measuring elements in the block diagram.
- Describe how a measurement system can be used in an automatic feedback system?
- 2. How can you measure linear and angular displacement by resistive sensor? State the characteristics of resistive sensors?

(10+8+7=25)CO₂

What is a capacitive sensor? What are the different parameters that can change the capacitance value? In order to monitor the water level, how can this sensor be used?

PO1,PO2, PO10

- Explain Photo-emissive transducers with necessary diagram. How a photo transistor can be used to count the cans in a conveyer belt?
- 3. A proportional controller is used to control the height of water in a tank where the water level can vary from 0 to 4.0 m. The required height of the water is 3.5 m, and the controller is to close a valve fully when the water rises to 3.9 m and open it fully when the water falls to 3.1 m.

(18+7=25)CO₄ PO1,PO10

Explain the controlling action with a schematic and flow diagram.

- ii. Do you think that Time Proportional Control is needed for the above case? Justify your comment with a proper diagram.
- iii. What will be the effect of Proportional Band on this process performance?
- **b.** What are the limitations of two-step (on/off) control, and in what situation such a control system is commonly used?
- **4 a.** State the advantages and application areas of fluid power and explain them briefly.

(5+10+10=25) CO3 PO1,PO2

- b. Draw a schematic diagram of Vane Pump and mention its nomenclature. Deduce the equation of maximum possible eccentricity and maximum volumetric displacement and establish a relationship between e_{max} and $V_{D\,max}$.
- c. i. A vane pump is to have a volumetric displacement of 100 in³. It has a rotor diameter of 20 inch, a cam ring diameter of 30 inch, and a vane width of 5 inch. What must be the eccentricity?
 - ii. A vane pump has a rotor diameter of 2000 mm, a cam ring diameter of 7500 mm, and a vane width of 550 mm. If the eccentricity is 28 mm, determine the volumetric displacement.
- 5 a. Explain the working principle of single acting and double acting cylinder with appropriate diagram and state the equations for extending stroke and retracting stroke.

(10+7.5+7.5=25) CO3 PO1,PO2

- **b.** A pump supplies oil at 20 gpm to a 2-in-diameter double-acting hydraulic cylinder. If the load is 1000 lb. (extending and retracting) and the rod diameter is 1 in, determine.
 - i. The hydraulic pressure during the extending stroke
 - ii. The piston velocity during the extending stroke
 - iii. The cylinder horsepower during the extending stroke
 - iv. The hydraulic pressure during the retraction stroke
 - v. The piston velocity during the retraction stroke
 - vi. The cylinder horsepower during the retraction stroke
- c. A hydraulic motor has a displacement of 10 in³ and operates with a pressure of 1000 psi and a speed of 2000 rpm. If the actual flow rate consumed by the motor is 95 gpm and the actual torque delivered by the motor is 1500 in ·lb., find
 - i. η_u
 - ii. η_m
 - iii. no
 - iv. The actual horsepower delivered by the motor

PO₃

- **b.** Explain the **control of a double-acting hydraulic cylinder** by drawing the schematic diagram using proper ANSI symbols.
- c. 1. Explain the working principle of the regenerative hydraulic circuit of Fig 1.
 - 2. A double-acting cylinder is hooked up in the regenerative circuit of Fig 1.




Fig: 1

The cracking pressure for the relief valve is 1000 psi. The piston area is $25 in^2$ and the rod area is $7 in^2$. The pump flow is 20 gpm. Find the cylinder speed, load-carrying capacity, and power delivered to the load (assuming the load equals the cylinder load-carrying capacity) during the

- i. Extending stroke
- ii. Retracting stroke

......END.....